

# duinotech

## Raspberry Pi 3.5in Touchscreen with Stylus & Enclosure XC4631 User Manual

Perfect for prototyping or a setting up a portable machine, the 3.5in touchscreen LCD display requires minimal setup. Includes a handy stylus and protective case.

### Specifications

<b>LCD Type</b>	TFT
<b>LCD Interface</b>	SPI
<b>Touch Screen Type</b>	Resistive
<b>Touch Screen Controller</b>	XPT2046
<b>Colours</b>	65536
<b>Backlight</b>	LED
<b>Resolution</b>	480 x 320 Pixel

### What's Included

- 1 x LCD Touchscreen
- 1x Stylus
- 1x Enclosure

### Essential Accessories

XC9001 – Raspberry Pi 3B+

### Installation

To setup the screen, the drivers will need to be downloaded & installed using the following commands in their respective order. You can either use the HDMI out on the Raspberry Pi or SSH for the setup process.

```
git clone https://github.com/jaycar-electronics/XC4631
```

```
cd XC4631/XC4631
```

```
sudo chmod +x LCD35-show
```

```
sudo ./LCD35-show
```

Distributed by: TechBrands by Electus Distribution Pty. Ltd. 320 Victoria Rd, Rydalmere NSW 2116 Australia Ph: 1300 738 555  
Int'l: +61 2 8832 3200  
Fax: 1300 738 500  
www.techbrands.com

Made in China